



ELECTRONICS, INC.  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089  
<http://www.nteinc.com>

## NTE1419 Integrated Circuit Head Amp Circuit for VCR

**Features:**

- Video Signal Pre-Amplifier Circuit
- Filter Amplifier Circuit
- Mixer Amplifier Circuit
- Head Switch Over Circuit
- Supply Voltage, either 9V or 12V

**Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$ , unless otherwise specified)

Supply Voltage, $V_{CC}$ .....	14.4V
Power Dissipation, $P_D$ .....	530mW
Operating Temperature Range, $T_{opg}$ .....	$-20^\circ$ to $+70^\circ\text{C}$
Storage Temperature Range, $T_{stg}$ .....	$-40^\circ$ to $+150^\circ\text{C}$

**Electrical Characteristics:** ( $T_A = +25^\circ\text{C}$ ,  $V_{CC} = 12\text{V}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Supply Current	$I_1$		26	–	44	mA
Voltage Gain (Head Amp)	$G_{V(1)}$	$f = 4\text{MHz}$ , $v_i = 1\text{mV}_{p-p}$	50.5	–	62.5	mA
	$G_{V(1)}$		50.5	–	62.5	mA
Voltage Gain (Mix Amp)	$G_{V(3)}$		10	–	14	dB
Second Harmonic Distortion (Head Amp)	$D_{2(1)}$		–	–	–40	dB
	$D_{2(2)}$		–	–	–40	dB
Input Noise Voltage	$V_{ni(1)}$	$f = 1\text{MHz}$ , B.P.F	–	–	2	$\mu\text{V}_{rms}$
	$V_{ni(2)}$		–	–	–2	$\mu\text{V}_{rms}$
Sensitivity	S		300	–	–	$\mu\text{A}$

### Pin Connection Diagram

